

Bausatz 2 ele Yagi 144 MHz mit 0,80m Boom im 28 Ohm Design
Antenna kit 2 ele Yagi 144 MHz with 0,80m boom in 28 Ohm Design
Breitbandausführung / Broadband version (144-146 MHz)

Antennenabmessungen / Dimensions table			
	Durchmesser Diameter (mm)	Länge / Length (mm)	Position (mm)
Strahler / Radiator	10	1002	480
Direktor / Director	8	926	690

Version 1 (V1): Vertikale Vormastmontage ca. 480 mm vor einem Mast
 Vertical pre mast mounting about 480 mm in front of a mast
 Gewinn/Gain: ca. 5,1 dBd V-R / F-B: 21,6 dB
 SWR Feinabstimmung durch Abstand zum Mast möglich
 SWR fine tuning through mast-radiator distance possible

Version 2 (V2): Horizontal am Mast montiert
 Mounted horizontal in front of a mast (stand alone)
 Gewinn/Gain: ca. 4,4 dBd V-R / F-B: 14,1 dB

